# **USER MANUAL QUICK INSTALLATION GUIDE**

# MGR450B



**BLUETOOTH®** (Audio Streaming) **Marine Gauge Digital Media AM/FM Receiver** 

FEATURING ZERO STANDBY CURRENT DRAIN







# **USER MANUAL** QUICK INSTALLATION GUIDE

# MGR450B

BLUETOOTH® MARINE GAUGE DIGITAL MEDIA AM/FM RECEIVER

iPod® and iPhone® are registered trademarks of Apple Inc registered in the USA and other countries.



BOSS Audio Systems 3451 Lunar Court • Oxnard, CA 93030

www.bossaudio.com 800-999-1236 US Toll-free 805-751-4853 Customer Service

Tech Support: www.bossaudio.com/support/technical-support






Thank you for purchasing this

3922

MGR450B Bluetooth Marine Gauge Digital Media AM/FM Receiver

Please read thorough these instructions carefully so you will know how to operate your model properly. After you have finished reading the instructions, keep this document in a safe place for future reference.

## THIS PACKAGE CONTAINS



# INFORMATION TO THE USER

# Bluetooth

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks is under license. Other trademarks and trade names are those of their

# FCC COMPLIANCE STATEMENT

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of this device.

This transmitter must not be co-located or operated in conjunction with any other antenna or transmitter. The Bluetooth antenna cannot be removed (or replaced) by user. This equipment complies with FCC/ IC radiation exposure limits set forth for an uncontrolled environment and meets the FCC radio frequency (RF) Exposure Guidelines and RSS-102 of the IC radio frequency (RF) Exposure rules. This equipment has very low levels of RF energy that it deemed to comply without maximum permissive exposure evaluation (MPE). But it is desirable that it should be installed and operated keeping the radiator at least 20 cm or more away from person's body (excluding extremities: hands, wrists, feet and ankles). Alteration or modifications carried out without appropriate authorization may invalidate the user's right to operate the

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions. may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Relocate or reorient the receiving antenna.
- Increase the separation between the equipment and receiver. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected
- Consult the dealer or an experienced radio/TV technician for help.

## !! WARNING !!

ADJUSTMENT OR ALTERATIONS OF THIS DEVICE MAY RESULT IN HAZARDOUS RADIATION EXPOSURE.

# IMPORTANT SAFETY PRECAUTIONS

# BE SURE TO OBSERVE THE FOLLOWING GUIDELINES:

- · Do not turn up the volume so high that you can't hear what's around you.
- · Use caution or temporarily discontinue use in potentially hazardous situations.
- Do not operate mobile video equipment while driving a motorized vehicle - safe driving and safety consideration of others should always be your highest priority.
- · Set your volume control at a low setting, then slowly increase the sound until you can hear it comfortably without distortion, or ear
- In the event you should notice smoke, strange noises or odor from this product, or any other abnormal signs, immediately turn off the power and consult your dealer or the nearest authorized **BOSS AUDIO Service Center** Using this product in this condition may result in permanent damage to the system

# **BEFORE YOU START INSTALLATION PRECAUTIONS**

# Always consult with a professional installer

- Installation or servicing of this product by persons without professional training and experience in electronic equipment and motorized vehicle accessories may be dangerous and could expose you to the risk of electric shock, injury or other hazards
- · When wiring directly to the vehicles battery, be sure to disconnect the batteries negative terminal wire before starting any wiring procedures, if extending the main power primary wire, it is suggested that an optional fuse and fuse holder (not included) with minimum rating of 20 Amperes be in-line with the positive battery
- The ground cable length should be as short as possible, if
- submerged in or under water under any circumstances

6006p

To avoid potential shorts in the electrical system, be sure to disconnect the (-) battery cable before installation. Use this unit with a 12-Volt battery and negative grounding only. Failure to do so may result in a fire or malfunction.



WIRE DIAGRAM

When replacing the fuse, be sure to only use of fuse of the rating specified on this product. To avoid short-circuiting, cover any disconnected leads with insulating tape. It is specially impor-

tant to insulate any unused wires, which if left uncovered may cause a short circuit. When connecting other devices to this product, refer to the manual for the product to be connected. The black cable is ground, make sure to connect the ground wire first.

Ensure that the ground cable is properly connected to metal parts of the vehicles body frame or direct to the battery if your vehicle does not have a grounded chassis frame. The ground cable of this units power amp and a second powered system must be connected to the frame separately with different screws. If the screw for the ground wire loosens or falls out, it could result in fire or malfunction.


# TROUBLESHOOTING GUIDE

TPOURIE CAUSE

IROUBLE	CAUSE	SOLUTION
	The fuse is blown	Check / replace the fuse
Unit will not turn on	Ignition not engaged	Turn ignition to on position
	Blown speaker	Replace faulty speaker
	Volume is low / muted	Press the volume level up
No sound is heard	Device is paused or muted	Check your devices playing / volume status
	The Bluetooth function of the device is not enabled	Refer to the user manual of the device for how to enable the Bluetooth function
Cannot pair Bluetooth	The MGR450B BT memory is full	Follow how to reconnect a device in section E
The audio quality is poor after connection with a Bluetooth enabled device	The Bluetooth reception is poor	Move the device closer to the audio system or remove any obstacle between the device and the systems antenna
	Power glitch or interference	Disconnect power for 10 seconds to reset
Unit has become	Low battery power	Charge battery, run the engine to recharge the battery
unresponsive	Reset the main system	Follow steps in section B

# **TECHNICAL SUPPORT**

1-805-751-4853 www.bossaudio.com/support



# **SPECIFICATIONS**

MOSFET

Channels: 4

Class: AB

40 stable

(All channels driven)

MAX Continuous Output: 240W

PEAK Power Rating: 60W / channel

Frequency Response: 20-20kHz

Button Backlight Illumination: BLUE LED

F/R/S RCA Preamp Output: 2VRMS

Grounding System: Negative type

· 3-way protection circuitry (thermal,

Unit Weight: 1.08lbs / 0.52kg

-22°F to 176°F / -30°C to 80°C

-4°F to 158°F / -20°C to 70°C

Maximum Current Consumption: 15A

overload, and speaker short protection)

RCA Input Impedance: 10kΩ

LCD: TN Type / Active Matrix

Power Source: 14.4VDC

(10.8V ~ 16V allowable)

Storage Temperature

# M TUNER FREQUENCY RANGE

- USA 87.5~107.9MHz Europe 87.5~108MHz
- Asia 87.5~108MHz
- Australia 87 5~108MHz
- Usable Sensitivity: 12dB (S/N=30dB)
- Bands: 2

#### AM TUNER FREQUENCY RANGE

- USA 530~1710KHz Europe 522~1620KHz
- Asia 522~1620KHz Australia 522~1620KHz
- Usable Sensitivity: 40dB (S/N=20dB) Bands: 1

## VEATHER BAND SELECTION

- CH 1 162 400MHz
- CH 2 162 425MHz
- CH 3 162 450MHz CH.4 162.475MHz
- CH 5 162 500MHz
- CH.6 162.525MHz
- CH.7 162.550MHz

# Bands: 1 RI LIFTOOTH

# BT: 3.0

# BT Range: 33Ft / 10M (Class 2)

- BT Profiles: A2DP / AVRCP 1.3
- Replacement Fuse: 15A

(Replace with AGU Fuse Type Only)

# ISB DRIVE MEDIA SUPPORTED

- 65,000 Songs
- 32GB / FAT 32
- USB 2.0 High Speed

Specifications subject to change without notice

**QUICK START GUIDE** 

Make the mounting hole size as follows **CAUTION!!** Using other mounting methods may void this warranty Install studs mounts into rear of chassis Adjust M4 nuts for the best mounting depth

**SUGGESTED MOUNTING METHODS** 

Snap off break-away tabs to best fit your applications depth

6 Secure and waterproof the wiring


Slip the unit through the hole cutout and into U-bracket

# **TOOLS NEEDED:**

- Wrench and/or Pliers
- Crimp Tool

# Measuring Tape / Ruler

Firmly tighten remaining M4 nuts




Refer any repairs to a qualified BOSS AUDIO SYSTEMS Service


• The MGR450B should be wired directly to a vehicles battery terminal

extending from you battery, be sure to use a proper gauge rating for the length of the run, use only high quality copper primary type wire • The MGR450B has a IPX6 weather resistant design, it should not be

Do not use abrasive cleaning materials on the lens or bezel







**CAUTION!!** Do not ground or short the speaker leads

# \*





# **SOURCE MODES**





B





All rights reserved. No part of this publication may be reproduced, distributed, or transmitted in any form or by any means, including photocopying, recording, or other electronic or mechanical methods, without the prior written permission of BOSS AUDIO SYSTEMS Inc.

Returns to previous item

# **TUNER SETUP**

**GETTING STARTED** 





# Short press to mute restore volume Turn the unit on, press and hold again to turn the unit off Press to pause, press again to resume playback Tuner/Weather Band Mode: Press to enter into Manual Seek mode, press and hold to enter into Auto Seek mode Media Playback Mode: Press to Track Up/Down, press and hold for Fast/Forward/Rewind SRC Press to scroll and select available Source PRESET Press to scroll and select Presets 1 ~ 6 Press and hold to enter into Tuner Function modes A-STORE / M-STORE / LOCAL / AREA / RDS / AF / TA / PTY Press to decrease volume, press to increase volume ◆ Tuner/Weather Band Mode: To change different band, press and hold to access Auto Store mode, the strongest stations of the selected band will be saved in preset channel automatically (FM1, FM2, AM1, WB1) Media Playback Mode: Press to access into search Folder/File music mod DISP Tuner Mode: Press to view RDS receiver information ENTER Media Playback: Press to view ID3 information AUDIO Press to access into the Audio Menu mode for adjustments EQ / XBASS / BASS / MIDDLE / TREBLE / BALANCE / FADER / READOUT / SUBW / SUBW LPF / SUBW LEVEL Press and hold to access into the System Menu. BT RECONNECT / BEEP ON/OFF / ABOUT / RESET

# **AUDIO and SYSTEM SETUP AUDIO** Short Press $\begin{array}{c} \text{AUJIO} \xrightarrow{-} \\ \text{EQ} & \text{ROCK} \end{array} \rightarrow \begin{array}{c} \text{AUJIO} \xrightarrow{-} \\ \text{EQ} & \text{FCAL} \end{array} \rightarrow \begin{array}{c} \text{AUJIO} \xrightarrow{-} \\ \text{EQ} & \text{USER} \end{array}$ xBass On/Off **BASS Level** MID Level Treble Level **Balance Level**

Fader Level


Subwoofer Settings

Mode	
Repeat	<ul> <li>ALL: to repeat all tracks on the storage media</li> <li>Song: the current track will be repeated</li> <li>Folder: repeats all tracks in the current folder</li> </ul>
Random On/Off	This function allows you to play track/songs from the current album, songs or artist in a random order
Tuner Mode	Selectable Settings
Auto Store	Press to access into A-STORE mode, the strongest stations of the selected band will be saved in FM 1 or FM 2, AM 1 BAND presets automatically
anual Store	When a desired radio station is set, press M-STORE to save it in the memory, you can store a total of 12 FM or 6 AM
ocal On/Off	ON: only stations with strong signal can be broadcast The local indicator will light up OFF: Stations of both strong and weak signals can be broadcast
Area	Select suitable country area for this unit: USA / EUROPE / ASIA / AUST
RDS On/Off	Turn On or Off the RDS function
AF On/Off	<ul> <li>ON: The unit will search for another station with stronger signal, but with the same program identification as the current station automatically</li> </ul>

AUDIO	→ <u>BTDISCÖ-</u>		
Long Press	→ SUSTEM - ON -	System— BEEP OFF	
	SUSTEM -		
	→ Saziew — — — — — — — — — — — — — — — — — — —	OF THE PROPERTY OF THE PROPERT	

To avoid battery exhaustion be sure to run the vehicles engine while using this product. Using this product without running the engine can drain the battery

SYSTEM



Item	Selectable Settings	
BT₊J	This feature allows Reconnect or Disconnect to the paired mobile phone or Bluetooth device manually	
BEEP←	Turn On or Off beep sound	
RESET←	To restore the factory default settings	
ABOUT-	To view the device hardware and software versions	



# RADIO OPERATION

- 1) Press the SRC button to select RADIO
- 2) Press ▶/II to MUTE, press again to UNMUTE
- REDIO SUBWAIL PE 10350 3) To advance stations press
  - 4) To skip previous stations press
  - 5) Press the button to display RADIO information
  - 6) Press the PRESET button to recall PRESETS 1 ~ 6



# **BLUETOOTH OPERATION**

# PAIRING & DISCOVERING A NEW BLUETOOTH CONNECTION

Note: The mobile device must be within 33ft (10m) of the MGR450B for Bluetooth to function properly.

SYSTEM .... 1) Power on the MGR450B by pressing and holding down the Power button for 1 second, the Bluetooth ICON will start to flash signalling that the MGR450B is now ready for Bluetooth pairing.

NOTE: You have 2 minutes before you must restart this procedure over again.

2) Now that the MGR450B is in pairing mode:

## ANDROID users:

- a. Go into the Settings Menu of your ANDROID device
- b. Enter the Bluetooth Menu and press SCAN
- c. "Boss Audio MGR450B" will now be display under AVAILABLE DEVICES
- d. If prompted, enter passcode: "0000"

# iOS users:

- a. Go into the Settings Menu of your iOS device
- b. Enter the Bluetooth Menu
- c. "Boss Audio MGR450B" will now be displayed
- d. If prompted, enter passcode: "0000"
- 3) If the MGR450B is not seen, repeat the above steps to refresh the "Device List"
- 4) When the BT connection is successful you will see BT CONNECTED message on the MGR450B LCD display, you are now ready to stream music from your devices favorite media player to the MGR450B



## RECONNECTION

- 1) Power on the MGR450B and your last paired device Bluetooth
- 2) The unit will now automatically be reconnected
- 3) If your device was previously paired with the MGR450B, but it wasn't the last paired device:
  - a. Ensure no other devices are currently paired
  - b. Press and hold MENU button to manually connect / reconnect to the MGR450B
- 4) If the device is out of range from the MGR450B, it will disconnect automatically:
- 5)The MGR450B will reconnect to the device once in range, a confirmation message will be displayed on the LCD



# BLUETOOTH STREAMING MUSIC

1) Press the SRC button to select BT AUDIO



- 2) Press ▶/II to start PLAY, press again to PAUSE
- 3) To skip songs or advance tracks press , press and hold to FAST FORWARD
- 4) To select the previous track press the button | , press and hold to FAST REWIND
- 5) Press the button to display song ID3 information



# **USB OPERATION**

1) Press the SRC button to select USB



2) Press ▶/II to start PLAY, press again to PAUSE

- 3) To skip songs or advance tracks press , press and hold to FAST FORWARD
- 4) To select the previous track press KM, press and hold to FAST REWIND
- 5) Press the button to display song ID3 information



# **AUX-INPUT**

1) Press the SRC button to select AUX IN

2) Press enter to MUTE, press again to UNMUTE AUX-IN EN HILL



Ensure to adjust the level of your devices master volume to 75%